

## NAMEPLATE DATA ENTRY

ELWOOD dNameplate\_H-3016-N-H\_Doc

February 14, 2017

The screenshot shows the 'Axis Properties' dialog box with the 'Motor Device Specification' tab selected. The left sidebar lists categories: General, Motor (selected), Model, Motor Feedback, Scaling, Hookup Tests, Polarity, Autotune, Load, Backlash, Compliance, Position Loop, Velocity Loop, Torque/Current Loop, Planner, Homing, Actions, Drive Parameters, Parameter List, Status, Faults & Alarms, and Tag. The main area contains the following fields:

**Motor Device Specification**

Data Source: Nameplate Datasheet (dropdown) [Parameters...]  
Catalog Number: <none> [Change Catalog...]  
Motor Type: Rotary Permanent Magnet (dropdown)  
Units: Rev (dropdown)

**Nameplate / Datasheet - Phase to Phase parameters**

Rated Power:	0.75	kW	Pole Count:	6	
Rated Voltage:	230	Volts (RMS)			
Rated Speed:	5000	RPM	Max Speed:	5000	RPM
Rated Current:	6.8	Amps (RMS)	Peak Current:	20.4	Amps (RMS)
Rated Torque:	2.3	N-m	Motor Overload Limit:	100.0	% Rated

Buttons at the bottom: Manual Tune..., OK, Cancel, Apply, Help.

## NAMEPLATE DATA ENTRY

ELWOOD dNameplate\_H-3016-N-H\_Doc

February 14, 2017

**Axis Properties**

Categories:

- General
- Motor
  - Model**
  - Motor Feedback
  - Scaling
  - Hookup Tests
  - Polarity
  - Autotune
- Load
  - Backlash
  - Compliance
- Position Loop
- Velocity Loop
- Torque/Current Loop
- Planner
- Homing
- Actions
- Drive Parameters
- Parameter List
- Status
- Faults & Alarms
- Tag

**Motor Model Phase to Phase Parameters**

Torque Constant (Kt):	0.4	N-m/Amps(RMS)
Voltage Constant (Ke):	24.0	Volts(RMS)/KRPM
Resistance (Rs):	1.30	Ohms
Inductance (Ls):	0.0034	Henries

**Flux Saturation Profile**

Flux Saturation @ 12.5%:	100.0	% Nominal Inductance
Flux Saturation @ 25.0%:	100.0	% Nominal Inductance
Flux Saturation @ 37.5%:	100.0	% Nominal Inductance
Flux Saturation @ 50.0%:	100.0	% Nominal Inductance
Flux Saturation @ 62.5%:	100.0	% Nominal Inductance
Flux Saturation @ 75.0%:	100.0	% Nominal Inductance
Flux Saturation @ 87.5%:	100.0	% Nominal Inductance
Flux Saturation @ 100%:	100.0	% Nominal Inductance

Manual Tune...

OK Cancel Apply Help

## NAMEPLATE DATA ENTRY

ELWOOD dNameplate\_H-3016-N-H\_Doc

February 14, 2017

The screenshot shows the 'Axis Properties' dialog box with the 'Motor Feedback Device Specification' tab selected. The left sidebar contains a tree view of categories: General, Motor (expanded), Model, Motor Feedback (selected), Scaling, Hookup Tests, Polarity, Autotune, Load (expanded), Backlash, Compliance, Position Loop, Velocity Loop, Torque/Current Loop, Planner, Homing, Actions, Drive Parameters, Parameter List, Status, Faults & Alarms, and Tag. The main area displays the following settings:

Property	Value	Unit / Description
Device Function:	Motor Mounted Feedback	
Feedback Channel:	Feedback 1	
Type:	Digital AqB with UVW	
Units:	Rev	
<b>Digital AqB with UVW</b>		
Cycle Resolution:	2000	Feedback Cycles/Rev
Cycle Interpolation:	4	Feedback Counts per Cycle
Effective Resolution:	8000	Feedback Counts per Rev
Startup Method:	Incremental	
<b>Commutation</b>		
Offset:	0.0	Degrees

Buttons at the bottom: Manual Tune..., OK, Cancel, Apply, Help.