

NAMEPLATE DATA ENTRY

ELWOOD dNameplate_N-5637-2-H

September 28, 2022

The screenshot shows the 'Axis Properties' dialog box with the 'Motor Device Specification' tab selected. The left sidebar contains a tree view with categories: General, Motor (selected), Model, Motor Feedback, Scaling, Hookup Tests, Polarity, Autotune, Load, Backlash, Compliance, Position Loop, Velocity Loop, Torque/Current Loop, Planner, Homing, Actions, Drive Parameters, Parameter List, Status, Faults & Alarms, and Tag. The main area displays the following fields:

Motor Device Specification

Data Source: Nameplate Datasheet (dropdown) [Parameters...]
Catalog Number: <none> [Change Catalog...]
Motor Type: Rotary Permanent Magnet (dropdown)
Units: Rev (dropdown)

Nameplate / Datasheet - Phase to Phase parameters

Rated Power:	1.6	kW	Pole Count:	4	
Rated Voltage:	230	Volts (RMS)			
Rated Speed:	4000	RPM	Max Speed:	4000	RPM
Rated Current:	8.1	Amps (RMS)	Peak Current:	24.3	Amps (RMS)
Rated Torque:	4.5	N-m	Motor Overload Limit:	100.0	% Rated

At the bottom, there is a 'Manual Tune...' button on the left and 'OK', 'Cancel', 'Apply', and 'Help' buttons on the right.

NAMEPLATE DATA ENTRY

ELWOOD dNameplate_N-5637-2-H

September 28, 2022

Axis Properties

Categories:

- General
- Motor
 - Model**
 - Motor Feedback
 - Scaling
 - Hookup Tests
 - Polarity
 - Autotune
- Load
 - Backlash
 - Compliance
- Position Loop
- Velocity Loop
- Torque/Current Loop
- Planner
- Homing
- Actions
- Drive Parameters
- Parameter List
- Status
- Faults & Alarms
- Tag

Motor Model Phase to Phase Parameters

Torque Constant (Kt):	0.71	N-m/Amps(RMS)
Voltage Constant (Ke):	42.42	Volts(RMS)/KRPM
Resistance (Rs):	1.0	Ohms
Inductance (Ls):	0.0052	Henries

Flux Saturation Profile

Flux Saturation @ 12.5%:	100.0	% Nominal Inductance
Flux Saturation @ 25.0%:	100.0	% Nominal Inductance
Flux Saturation @ 37.5%:	100.0	% Nominal Inductance
Flux Saturation @ 50.0%:	100.0	% Nominal Inductance
Flux Saturation @ 62.5%:	100.0	% Nominal Inductance
Flux Saturation @ 75.0%:	100.0	% Nominal Inductance
Flux Saturation @ 87.5%:	100.0	% Nominal Inductance
Flux Saturation @ 100%:	100.0	% Nominal Inductance

Manual Tune...

OK Cancel Apply Help

NAMEPLATE DATA ENTRY

ELWOOD dNameplate_N-5637-2-H

September 28, 2022

The screenshot shows the 'Axis Properties' dialog box with the 'Motor Feedback Device Specification' tab selected. The left sidebar contains a tree view with categories: General, Motor (expanded), Motor Feedback (selected), Scaling, Hookup Tests, Polarity, Autotune, Load (expanded), Backlash, Compliance, Position Loop, Velocity Loop, Torque/Current Loop, Planner, Homing, Actions, Drive Parameters, Parameter List, Status, Faults & Alarms, and Tag. The main area displays the following settings:

Motor Feedback Device Specification		
Device Function:	Motor Mounted Feedback	
Feedback Channel:	Feedback 1	
Type:	Digital AqB with UVW	
Units:	Rev	
Digital AqB with UVW		
Cycle Resolution:	2000	Feedback Cycles/Rev
Cycle Interpolation:	4	Feedback Counts per Cycle
Effective Resolution:	8000	Feedback Counts per Rev
Startup Method:	Incremental	
Commutation		
Offset:	0.0	Degrees

Buttons at the bottom: Manual Tune..., OK, Cancel, Apply, Help.